



Bohrung für
Saitenerdung

Bridge-Humbucker
Polepiece-Abstand: 50.5 mm

Neck-Humbucker
Polepiece-Abstand: 49.0 mm

Elektronik-Fach

Kabelkanäle

Halswinkel = 3°
(an Bridge-Höhe anpassen)

10.5°

Seitenmarkierungen

Bundabstände 635mm Mensur

1	35,64	13	335,32
2	69,28	14	352,14
3	101,03	15	368,02
4	131,00	16	383,00
5	159,29	17	397,15
6	185,99	18	410,50
7	211,19	19	423,10
8	234,97	20	434,99
9	257,43	21	446,21
10	278,62	22	456,81
11	298,62	23	466,81
12	317,50	24	476,25

